

3307 Industrial 25th Street Fort Pierce, FL 34946 Phone: 772-429-0045 Fax: 772-429-0170

## Ionic Cleaner Model IC-1 (With Cleaning Solution)

## **Cleaning Instructions:**

Pour 2oz of the cleaning solution in the tank and mix the water. Plug transformer cord into the side of the IC-1, and then plug the transformer into an 110V/60Hz wall outlet. Place the fiber glass screen at the bottom of the tank. (Thoroughly rinse when solution is changed).

Attached one or more items to the hanger, and then connect the alligator lead to the hanger. The alligator lead should no be placed in the cleaning solution, only the hanger with the items to be cleaned should touch the solution. Press the ON button, the green light will be illuminated during operation. After the cleaning cycle has completed, the light will extinguish. This takes approximately 60 seconds. You may repeat the cleaning cycle several times if required. After each cycle, rinse the articles in clean water and dry with a soft cloth. Extremely dirty items can be soaked in the cleaning solution and a small brush may be used.

## Cautions

Some items require very short cleaning cycles, such as SILVER. It should be checked frequently to avoid darkening or tarnishing. Silver chains must not be allowed to touch itself during cleaning. If darkening occurs, rinse in water and use a soft cloth to remove tarnish.

In some cases, a darkened piece can be cleaned in a non-acid, Jeweler's Pickle or white vinegar.

We recommend you use less time cleaning until you learn how your jewelry responds to this high speed cleaning method. Remember no harm can be done by under cleaning your jewelry; tarnish is caused by over cleaning.

## Suggestions

This ionic cleaner is different from the ultra-sonic cleaner in it's high speed of cleaning. For optimum performance, we recommend that you experiment with this high speed cleaner, and soon you will be extremely happy with this fine tool.

This IC-1 unit is warranted for a period of one year. Warranty becomes void if the unit is opened.

Dymond, Inc., shall not be held legally liable or responsible for any damage by the unit. E.&O.E.